

BOOSTER 1700



Ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed.

It can be used as:

- An emergency starter.
- An additional power source for vehicles (memory saver).
- A multipurpose additional power source (for electrical 12V devices).

It is rechargeable by connecting it to the cigarette lighter of the vehicle or to the electricity network.

It can be stored in any position **without risking acid leakage.**

It comes with:

- 20 amps **automatic reset breaker**,
- **protection circuit against peak tensions** to protect the vehicle electronic system,
- **charge test button** with LEDs.

It delivers 1700 peak amps and a minimum of 600 constant amps.

INCLUDING, AS STANDARD: mains power supply LESA 5A, cigarette lighter re-charger cord, clamps with 6-wire copper cable.

PORTABLE START BOOSTER AND RECHARGEABLE POWER SOURCE

TECHNICAL DATA

Code	C00402
Item	BOOSTER 1700
Supply voltage (single-phase)	230V
Voltage	12V
Peak current output	1700A p
Constant current output	600A
Charge voltage	max 14,9 V
Automatic power supply	LESA 5A
Recharge voltage	12V 0,6 Ah
Charging cable 12V	LESA 1
Insulated clamps	YES
Sealed and maintenance free battery	12V 18Ah
Overload protection	YES
Number of batteries	1
Weight	10 kg
Dimensions	275x135x330h mm
Cable length	450 mm
Cables section	25 mm ²