

# BOOSTER 3100/6100



**INCLUDING, AS STANDARD:** power supply LESA 8, cigarette lighter re-charger cord, clamps with 6-wire copper cable

Ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed.

Designed for operating mostly at 12V and occasionally at 24V.

It can be used as:

- An emergency starter.
- An additional power source for vehicles (memory saver).
- A multipurpose additional power source (for electrical 12V or 24V devices).

It is rechargeable by connecting it to the cigarette lighter of the vehicle or to the electricity network.

It can be stored in any position **without risking acid leakage**.

It comes with:

- **protection fuses against short-circuits**,
- 20 amps **automatic reset breaker**,
- **protection circuit against peak tensions** to protect the vehicle electronic system,
- **charge test button** with LEDs.

## PORTABLE START BOOSTER AND RECHARGEABLE POWER SOURCE

### TECHNICAL DATA

Code	<b>C00408</b>
Item	<b>BOOSTER 3100/6100</b>
Supply voltage (single-phase)	230V
Voltage	12V 24V
Peak current output	6000A / 3000A p
Constant current output	1150A
Charge voltage	max 14,9 V
Automatic power supply	LESA 8
Recharge voltage	12V 4 Ah
Charging cable 12V	LESA 1
Insulated clamps	YES
Sealed and maintenance free batteries, nr. 2 units	12/24V 23Ah
Overload protection	YES
Number of batteries	2
Weight	20 kg
Dimensions	410x175x310h mm
Cables length	1550 mm
Cables section	50 mm <sup>2</sup>