

BOOSTER 1800



Ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed.

It can be used as:

- An emergency starter.
- An additional power source for vehicles (memory saver).
- A multipurpose additional power source (for electrical 12V devices).
- Suitable for frequent use.
- Suitable for vehicles with battery up to 100Ah.

It is rechargeable by connecting it to the cigarette lighter of the vehicle or to the electricity network. It can be stored in any position **without risking acid leakage**.

It comes with:

- 20 amps **automatic reset breaker**,
- **protection circuit against peak tensions** to protect the vehicle electronic system,
- **charge test button** with LEDS.

It delivers 1800 peak amps and a minimum of 600 constant amps.

INCLUDING, AS STANDARD: mains power supply LESA 6A, cigarette lighter re-charger cord LESA1 with LEDs, curved and highly adherent clips with 6-wire copper cable.

PROFESSIONAL START BOOSTER AND RECHARGEABLE POWER SOURCE

TECHNICAL DATA

Code	C00400
Item	BOOSTER 1800
Supply voltage (single-phase)	230V
Voltage	12V
Peak current output	1800A p
Constant current output	600A
Charge voltage	max 14,9 V
Automatic power supply	LESA 6A (12V 1,5 Ah)
Charging cable 12V	LESA 1
Insulated clamps	YES
Sealed internal battery	12V 18pro Ah
Overload protection	YES
Number of batteries	1
Cable length	870 mm
Cables section	25 mm ²
Shock proof body	A B S
Weight	8,800 kg
Dimensions Charging cable 12V	325x110x285h mm

We reserve the right to modify