

BOOSTER 3100



INCLUDING, AS STANDARD: power supply LESA 6A, cigarette lighter recharger cord, clamps with 6-wire copper cable, black clamp with LED.

Ideal for any application where a portable powerful quick-start or/and a long lasting power source is needed.

It can be used as:

- An emergency starter.
- An additional power source for vehicles (memory saver).
- A multipurpose additional power source (for electrical 12V devices).

It is rechargeable by connecting it to the cigarette lighter of the vehicle or to the electricity network.

It can be stored in any position **without risking acid leakage.**

It comes with:

- 20 amps **automatic reset breaker**,
- **protection circuit against peak tensions** to protect the vehicle electronic system,
- **charge test button** with LEDS.

It delivers 3100 peak amps and a minimum of 1150 constant amps.

PORTABLE START BOOSTER AND RECHARGEABLE POWER SOURCE

TECHNICAL DATA

Code	C00406
Item	BOOSTER 3100
Supply voltage (single-phase)	230V
Voltage	12V
Peak current output	3100A p
Constant current output	1150A
Charge voltage	max 14,9 V
Automatic power supply	LESA 6A
Recharge voltage	12V 1,5 Ah
Charging cable 12V	LESA 1
Insulated clamps	YES
Sealed and maintenance free battery	12V 23Ah
Overload protection	YES
Number of batteries	1
Weight	12 kg
Dimensions	410x135x310h mm
Cables length	1550 mm
Cables section	25 mm ²